

Fixture Type:

Project Name

Location:

Date:

Straight Square Steel Poles

Features:

- Straight square steel light pole
- Available side drilled for arm mounted area lighting luminaires or with tenon mounts for flood or post top luminaires
- Mounting heights of 10 to 30 feet can be used based on selected luminaire application
- Textured architectural bronzed powder coat finish

Specification:

CATALOG	HEIGHT	GAUGE	SIZE	BASE	BOLT CIRCLE	BOLT PROJ.	BOLT SIZE	WEIGHT (LBS)	EPA 70	EPA 80	EPA 90	EPA 100	EPA 110	EPA 120
	10ft		4″x4″	11"	8" - 10"	2.75"	3/4"x17"x3"	88	25.2	20.5	1 <i>7</i> .1	11.4	10.3	9.6
	1.5ft	11						117	15.2	12.5	10.1	8.5	6.9	5.4
LP-SS	20ft							152	9.2	7.3	6	4.2	3	1.6
	25ft							190	8.9	6.9	5.7	4.1	3.6	2.2
	30ft		5"x5"		10" - 12"	3.375"	3/4"x17"x4"	267	7.2	5.4	4.1	3.8	2.8	1.2



Ordering Guide

Example: LP-SS-30FT-4

Sku	Height	Size	Accessories Included:
LP-SS	10FT 15FT 20FT 25FT 30FT	4 = 4" 5 = 5"	LP-BMS=Anchor Bolt LP-SPP =Screw Positioning Plate LP-S4 =4" Base shield LP-S5 =5" Base shield

Rev 06-17-2024




Straight Square Steel Poles

Fixture Type: Project Name Location: Date:

Dimensions:

10FT	L = 3.0M	
15FT	L = 4.6M	
20FT	L = 6.1 M	
25FT	L = 7.6M	
30FT	L = 9.1 M	

LIGHT POLE TOP	
Removable Cap Arm Installation hole	Ø2.38*(60mm)ODX4*9101mm) LG 0.24*(6mm) THK.TENON MOUNT
PRE-DRILL MOUNT OPTIONS	TENON MOUNT INCLUDED ON TOP



Accessories:



Anchor Bolts (LP-BMS)

Before installing the lamp pole, the installation hook should be buried underground and fixed by cement After fixing, the lamp pole should be fixed by locking screw and base installed.



Positioning Plate (LP-SPP)

This is a screw rod positioning plate. After the screw rod of the lamp rod base is fixed underground, the positioning plate is fixed with the screw rod to prevent the screw rod from deviation. Finally, the lamp rod is locked.



4" or 5" Base Shield (LP-S4/LP-S5)

The 4" or 5" Installation of base shield is used to protect the base after fixing the lamp pole, so that the lamp pole base is not damaged, thereby increasing the service life of the lamp pole.

Rev 06-17-2024