

LED Linear High Bay

Fixture Type:	
Project Name	
Location:	
Date:	

Features

- Low profile light weigh design linear high bay make it easier and quicker to install.
- Rugged cold-rolled steel plate corrosion resistant housing enable superior thermal performance.
- Prismatic diffuser for maximum light output while reduce glare, optional aisle optic lens available.
- Wattage selectable and 2 CCT adjustable.
- Standard 6ft aircraft cable suspended mounting, optional for pendant mount or surface mount.
- Optional plug and play motion sensor and external emergency battery backup available.



















Dimensions



Net Weight 210W: 2.86kg (6.30 lbs) 225W: 3.96kg (8.73 lbs)



Specification

Material	Rugged cold-rolled steel	Efficacy	Up to 142 lm/W
Lens	Prismatic Lens/Aisle Lens	LED Life Span	50,000 hrs base on the TM-21 calculations
Beam angle	100 degree	Dimmable	0-10V Dimming
IColor Temp	2CCT 4000K/5000K	Lumen Package	12,000 lm to 30,000 lm
CRI	70	Warranty	5 Years
Input Voltage	120-277V or 347-480V	Ambient Operation Temperature	-40°C (-40°F) ~45°C (113°F)
Installation	Standard suspended mount 6ft aircraft cable included. Optional 12ft aircraft cable is available. Optional surface mount and pendant mount is available.	Listing	DLC Standard UL Listed Damp location listed




LED Linear High Bay

Fixture Type:	
Project Name	
Location:	
Date:	

Ordering Guide

Example: LHB4-UW3CCT-210W-EM15-MS01-WG210W-HC12



Optional Accessories



EM15 (SKU:EMBK-LHB-15W) = 15W Emergency battery backup, External pre-install.

EM40 (SKU:EMBK-LHB-40W) = 40W Emergency battery backup, external pre-install. MS01 (SKU: HD09VR-PIR) =Plug and play PIR motion sensor with dial switch.

MS02 (SKU:BL-ANT5-4T-MIC) = 12/24V Plug and play microwave motion sensor 3.5mm audio plug.

.BLMS01 (SKU:SILVAIR01)=Bluetooth motion sensor plug and play field install, work with SILVAIR APP. WG-210W (SKU:WG-LHB4-210W) = Wire guard for LHB4 210 Watt. (SKU:PB-LHB)
= Surface mount or pendant mount box

HC12 (SKU:HC-LHB12FT) = 12ft aircraft cable AISLE-LENS (SKU:LHB-AISLELENS) =Aisle optic lens

Note: 1. Surface mount/pendant mount is not support when the fixtures installed the emergency battery backup.



LED Linear High Bay

Fixture Type:	
Project Name	
Location:	
Date:	

Product Information

LHB4-UW3CCT-210W	400	0K	50	00K
WATTAGE	LUMEN	EFFICACY	LUMEN	EFFICACY
210W	30000 lm	140lm/W	30000 lm	140lm/W
172W	24000 lm	140lm/W	24000 lm	140lm/W
129W	18000 lm	140lm/W	18000 lm	140lm/W
86W	12000 lm	142lm/W	12000 lm	142lm/W


Prismatic Diffuser(Low Glare)(Default) Textured Diffuser(Aisle Optic)(Optional)





135







LED Linear High Bay

Fixture	Type
----------------	------

Project Name

Location:

Date:

Optional Accessories

Emergency Battery Backup:



External 15W Emergency Battery Backup

SKU: EMBK-LHB-15W

- External battery backup is pre-install by request
- 90 minutes emergency operation
- Provide up to 2,100 lumen during emergency mode



External 40W Emergency Battery Backup

SKU: EMBK-LHB-40W

- -External battery backup is pre-install by request
- 90 minutes emergency operation
- Provide up to 5,600 lumen during emergency mode

Motion Sensor:



PIR Plug and Play Manually Adjustable Motion Sensor 12V 3.5mm audio plug SKU:HD09VR-PIR

- -3.5mm audio plug passive infrared motion sensor.
- -With daylight harvesting and photocell function.
- -The rotating switch is built into the motion sensor and allows you to manually adjust the standby dimming level and hold time without needing a remote control.
- -Configure setting by remote control HD06R (sold separately).
- -Default setting Detection Area 100%, Hold time 5S, Daylight Threshold disable Standby Period OS, Standby Dimming Level 10%.



Microwave Plug and Play Motion Sensor 12/24V 3.5mm audio plug SKU: BL-ANT5-T4-MIC

- -3.5mm audio plug microwave motion sensor 12-24V DC
- Factory default setting: 100% sensitivity, Hold time 5min, Dimming level: 30%, Dimming time: 60mins.





Bluetooth mesh network PIR Plug and Play Motion Sensor

- SKU: SILVAIRO1
- PIR plug and play motion sensor
- -Bluetooth control work with Silvair app on IOS and Android.



LED Linear High Bay

Fixture	Type
----------------	------

Project Name

Location:

Date:

Wire Guard:



Wire Guard

SKU: WG-LHB4-210W - Wire guard for 210W LHB4

Mounting Option:



Surface Mount and Pendant mount Box

SKU: PB-LHB

-Surface mount/pendant mount kit for use LHB4 fixture.



12ft Aircraft Cable

SKU: HC-LHB-12FT

-12ft aircraft cable for suspended mount.