

LHB3 Series

LED Linear High Bay

| Fixture Type: | | | | | |
|---------------|--|--|--|--|--|
| Project Name: | | | | | |
| Location: | | | | | |

Date:

Features


- Durable extruded aluminum housing LED linear high bay
- Lumen packages ranging from 12600 lm to 50500lm
- Color temperature options 4000K or 5000K
- Polycarbonate lens with semi frosted diffuser provided
- Voltage is 120-277 & optional 347-480V
- Standard 1-10V dimming
- Standard steel wire rope mount
- Optional PIR motion sensor and emergency battery backup




Product Performance Standard

| Size | See Page2 for Detail | Power Factor | 90% |
|---------------|----------------------|----------------------------------|---------------------------------|
| Weight | 10 lb | Life Span | 50,000 Hrs |
| IP Rate | IP65 | Dimmable | 1-10V Dimmable |
| Color Temp | 4000K/5000K | Efficacy | Up to 140 lm/W |
| CRI | 70 | Warranty | 5 Years |
| Input Voltage | 120-277V/347-480V | Ambient Operation Temperature | -40C° (-40°F) ~ 45C° (113°F) |







175W/210W



300W



370W

| Fi | xture Type | | Wattage | | Color Temp. | | Voltage | Optional Accessories |
|----|------------|---|---------|---|-------------|---|------------------|--|
| | | — | | _ | | _ | _ | _ |
| | LHB3 | | 90W | | 40K = 4000K | | Blank = 120-277V | Blank = No accessories |
| | | | 130W | | 50K = 5000K | | HV = 347-480V | ¹ MS = PIR Motion Sensor |
| | | | 175W | | | | | (-BL-823PIR-IN) |
| | | | 210W | | | | | ¹ EM = Emergency Battery Backup |
| | | | 300W | | | | | Wire Guard |

Note: 1. Motion sensor and emergency battery backup only suitable for 120-277V







LHB3 Series

LED Linear High Bay


| Fixture Type: | | | | | |
|---------------|--|--|--|--|--|
| Project Name: | | | | | |
| Location: | | | | | |
| Date: | | | | | |

Product Information

| | 40 | 000К | 5000K | | |
|---------|---------|-----------------|---------|-----------------|--|
| WATTAGE | LUMEN | EFFICACY | LUMEN | EFFICACY | |
| 90W | 12600lm | 140lm/W | 12600lm | 140lm/W | |
| 130W | 18500lm | 142lm/W | 18500lm | 142lm/W | |
| 175W | 24500lm | 140lm/W | 24500lm | 140lm/W | |
| 210W | 30000lm | 143lm/W | 30000lm | 143lm/W | |
| 300W | 41500lm | 138lm/W | 41500lm | 138lm/W | |

Dimension

300W







LHB3 Series

LED Linear High Bay

| Fixture Type: | | | | |
|---------------|--|--|--|--|
| Project Name: | | | | |
| Location: | | | | |

Optional Accessories



Wire Guard



Emergency Battery Backup

- Emergency battery backup is field installed or pre-installed by request

Date:

-Delivery 900 limen for 90 minutes emergency operation




PIR - Motion Sensor

- -SKU:BL-823PIR-INT
- -Internal PIR Motion Sensor is field installed or pre-installed by request
- -Provide multi-level control based on motion or daylight contribution

For the accessories detail, please visit www. lironlighting.com/product_categories/add-on-accessories

Wiring Diagram





Scan the QR code or visit www.lironlighting.com/product/lhb3 for the complete luminare installation guide.

