## INSTALLATION INSTRUCTION MANUAL

## **Safety Precautions**

Read all safety precautions and installation instructions carefully before installing or servicing this fixture. Failure to comply with these instructions could result in potentially fatal electric shock and/or property damage.

It is recommended that all wiring be performed by a qualified electrician. This fixture must be wired in accordance with all national and local electrical codes.

Do not handle any energized fixture or attempt to energize any fixture with wet hands or while standing on a wet or damp surfaceor in water.

Make sure that the power source conforms to the requirements of the fixture (see labels on fixture housing).

To reduce the risk of electrical shock and to assure proper operation, this fixture must be adequately grounded. To accomplish proper grounding, there must be a separate ground wire (green) or bare metal contact (metal conduit) between this fixture and the ground connection of your main power supply panel.

This fixture is intended to be used for general outdoor lighting in damp or wet loations.

## **Assembly Instructions**

1.Disconnect electrical power before installing or servicing any part of fixture.

## 2. Wiring

Note:Most dwellings built before 1985 have supply wire rated to 60°C. Consult a qualified electrician before installing. This unit will not operate properly unless connected to a "grounded" electrical circuit. Electrical shock, over heating, low or no light output, and shortened LED life can result if proper grounding is not done.

- Wire connection: Connect white(neutral) supply wire to white
  to white fixture wire; connect black(hot) supply wire to black fixture wire,
  connect ground wire to cooper wire, using wire nuts provided.
   Pull on each wire lead to verify all connections are secure. Make sure
  no bare wires are exposed outside of the wire nuts.
- 3. Fasten fixture(3)to the base(4) using thumb screws (2)
- 4. Turn on power, confirm unit is operating properly.





